

CYBER 4-20mA/ XIN IP65 Head Plastic heads Instruction manual



T +39.02.9354.4190 E info@nenvitech.com www.nenvitech.com THIS MANUAL MUST BE CAREFULLY READ BY ALL PERSONS WHO HAVE OR WILL HAVE THE RESPONSIBILITY FOR INSTALLING, USING OR SERVICING THIS PRODUCT.

Like any equipment, this product will perform as designed only if installed, used, and serviced in accordance with the manufacturer's instructions.



OTHERWISE, IT COULD FAIL TO PERFORM AS DESIGNED AND PEOPLE WHO RELY ON THIS PRODUCT FOR THEIR SAFETY COULD SUFFER SEVERE PERSONAL INJURY OR DEATH.

The warranties made by N.E.T s.r.l. with respect to this product are voided if the product is not installed, used, and serviced in accordance with the instructions in this user guide. Please protect yourself and others by following them.

We recommend our customers to write or call us regarding this equipment prior to use or for any additional information relative to use or repair.



Summary

1.0	Introduction 4
1.1	General description4
2.0	Technical specifications
3.0	Mechanical Specifications6
4.0	Installation site pre arrangement7
4.1	General precautions7
4.2	Precautions based on the gas to detect and environmental inhibitors
4.3	Special conditions for safe use7
5.0	Installation
5.1	I/O Connections
5.2	Safety data9
5.3	4-20 mA output connection9
5.4	RS485 digital connection10
6.0	Testing and use
6.1	Power on
6.2	Testing
6.3	Use
7.0	Maintenance
7.1	Preventive maintenance routines11
7.2	Corrective maintenance routines11
7.3	Note on IP grade
7.4	Cleaning12
7.5	Disassembly instructions12
7.6	Trouble shooting guide12
8.0	Restorations
9.0	Packing instructions14
10.0	Warranty for repairing14
11.0	Instructions for disposal14



1.0 Introduction

These instructions refer to the installation, use and maintenance of CYBER 4-20mA (also named as CYBER OTH in case of OEM version) and XIN/DIN plastic head gas sensors.

1.1General description

CYBER 4-20mA and XIN/DIN head gas sensors are used to detect the presence of different gases in environments where the principal constituent is air.

The sensing element inside the CYBER 4-20mA detector can be either a catalytic sensor, an infrared sensor, or an electrochemical cell. XIN/DIN heads are supplied with only infrared sensor.

The industrial grade catalytic sensor (pellistor) employed for the detection of flammable compounds offers a great precision and selectivity with most of the explosive gases, thus avoiding false alarms. Infrared sensors are immune to poisoning produced by certain substances that inhibit and damage catalytic sensors. This allows you to add reliability and durability, allowing the use of detectors even in places where the pellistors cannot guarantee optimal functionality. Electrochemical cells are used to detect gases at low concentration, for this reason they are used to detect toxic gases.

CYBER 4-20mA and XIN/DIN heads are devices characterised by the presence of the sensing element and the electronics required to process the signal in the detector head. A multi-core cable with 6 conductors allows the connection to power supply and different outputs depending on the configuration of the detector.

To protect and increase the stability and accuracy of the gas detector, the microprocessor present on the internal electronic circuit board, is programmed with the following software algorithms:

- Self-diagnostic procedure to control the detector main operational parts, both hardware and sensing element.
- Zero-point tracking to maintain the zero parameter of the sensor apart from possible drifts due to thermal or physical variations of the sensor.
- Digital filter employed in the digital analysis of the analogue values sampled. It is designed to prevent the effects of transients, which may cause instability or incorrect readings with possible false alarms.
- Hysteresis cycle applied to the digital outputs to eliminate continuous switching close to the preset alarm thresholds.
- Watch-dog for the microprocessor control. In case of intervention, the output current drops down to 0mA (if present). If the RS485 interface is connected, the communication will be interrupted, while the Fault signal (if present) will be activated.



2.0 Technical specifications

Table 1) Technical specifications of gas sensors

	Product type:	CYBER 4-20mA	XIN/DIN 4-20mA	
	Sensing Element:	IR sensor, EC cell, catalytic bead	NDIRsensor	
	Operating temperature range	Electronics between -40°C / +60°C Sensing elements depend by the sensor technology (See Sensor specification)		
	Storage temperature range	Depend by the sensor technology (See Sensor specification)		
leral	Maximum temperature cycle variations	± 1°C/min		
Gen	Operating humidity range	0-95% NDIR & catalytic 20-90% EC cell	0-95% non condensing	
	Operating pressure range	800-1200 mBar NDIR sensor 900-1100 mBar EC cell & catalytic	800-1200 mBar	
	Enclosure	Acetal Copolymer IP rating: IP65		
	Calibration	Individually calibrated with tempera	ture compensation. Test report supplied.	
	Accessories	NECAP3: Aluminium calibration adapter. It allows the right quantity of gas inlet to flow to the detector.		
	Range	ppm; %vol;%lel	ppm; %vol	
ut	Response time	Depending on sensor type	<60 seconds	
reme	Digital to analog error	±3%F.S	±2%F.S	
easu	Digital error	±5%F.S	Depend by the sensor	
Š	Stabilization Time	At least 60 minutes		
	Warmup time	<120 seconds		
	Power Voltage	Nominal 12-24Vdc (-20% +15%)		
	Current Consuption @12V	20-25mA with EC cell 75-85mA with NDIR 40-60mA with catalytic bead	<80 mA Idc	
rical	Current Consuption @24V	25-35mA with EC cell 40-50mA with NDIR 20-30mA with catalytic bead	<40 mA Idc	
Elect	Warm up time	90 s for full operation @ 25 °C 1 hour for full specification @25°C	60 s for full operation @ 25 °C 1 hour for full specification @ 25 °C	
	Max output current	24 mA		
	Output load resistor range	330Ω with Vin between 12-15V 500Ω with Vin between 15-24V	100-350 Ω	
	DC output impedance	100 Ω	30 Ω	
	Analog output	4-20mA	4-20mA *not available in DIN version	
Signa Outpu	Digital communication	Modbus protocol RS485	Modbus protocol RS485	
	Baud Rate	9600 bps	4800;9600;19200;38400 bps	



CYBER 4-20mA/XIN-DIN Plastic IP65 Head **INSTRUCTION MANUAL**

MT5059 Rev.2

2.1 Label explanation

Here are following examples of the label of the product:







DISCHARGE SEE INSTRUCTIONS

Table 2 The data present on the product label are explained below			
N.E.T S.r.l.	Name of the manufacturer of the device		
NETC32/PB-XIN-IFL32-54BL	Example of identification code		
HEAD	Product model		
Thread: ¾" NPT	Thread type		
IEC 60335-2-40:2022 or IEC60079-29-1:2016	Present in case of products tested over Annex LL of IEC 60335-2-40:2022 or IE60079-29-1 standard		
Gas: R454b	Example of gas to be detected		
F.S: 7.7%Vol	Example of measuring range		
-40°C≤T≤+60°C	Temperature range of the product		
Output: 4-20 mA	Signal output		
Vin: 12-24 Vdc	Power supply		
Cyber S/N: XXXXX	Serial Number present only in case of Cyber products (codes: AIN, ATX or AFL)		
Sensor batch: XXXXXX	Sensor Batch		
IP65	IP degree of protection (1st number: protection against solids, 2nd number: protection against liquids)		

3.0 Mechanical Specifications



All dimensions are expressed in mm.

Standard length of the cable is 25cm, other lengths are available on customer's request.





4.0 Installation site pre arrangement 4.1 General precautions

At the mounting and installation phase, be sure all safety precautions have been considered. Always remember how important the correct positioning of gas sensors is to get the optimum response. Be careful:

- > never to install gas sensors close to air intakes or fans causing strong air currents.
- the detectors are attached to a firm base to prevent vibration that can damage them, producing unreliable results. Although the electronics comply with the electromagnetic compatibility rules, it is advised to keep the detectors at a distance from any radio frequency senders (such as radio links or similar).
- those detectors are placed in a convenient location for future maintenance and calibration requirements.

4.2 Precautions based on the gas to detect and environmental inhibitors

When preparing the installation site, it is necessary to consider the nature of the gas to be detected and the presence of chemical agents in the environment.

- All the gases lighter than air (Methane, Hydrogen, Ammonia) tend to spread upwards; the sensor should be placed at 30 cm from the ceiling to maximise the effectiveness of the detection. All the gases heavier than air (LPG, Butane, Petrol Vapours) tend to spread downwards; the detector should be placed at 30 cm from the floor.
- Catalytic sensors (Pellistors) offer excellent output linearity up to 100% LFL and have an estimated lifetime of 4 years. Catalytic sensor performance may be altered by the presence of some substances that, when present in the atmosphere being analysed, can considerably change the response of the sensor, and even damage it irremediably. The presence of inhibitors or poisons is the most common cause of problems in the gas detection, and, for this reason, it is necessary to pay attention to avoid any contamination. Among the most common poisons or inhibitors we can list silicones, tetraethyl lead, sulphurous compounds (hydrogen sulphide), chlorinated compounds (carbon tetrachloride), trichloroethylene and halogenated hydrocarbons. These compounds do not affect the Infrared sensor, which find a suitable application whenever a flammable gas is to be detected in environments where Pellistor cannot work. This new technology has undoubted advantages such as lower dependence from environmental factors.

WARNING!

Do not use gas sensors in atmospheres with an oxygen concentration greater than 21%.

4.3Special conditions for safe use

- The supply cable of the gas detector must be protected against mechanical damages caused by impact or friction.
- Power supply must be guaranteed to a stable level without presence of spikes or interruption of the power level.



5.0 Installation

The installation should be performed by qualified personnel, consider as example the EN 60079-14 standard. It is strictly recommended the use of personal protective equipment during operations inside the enclosure.

The enclosure of the sensor and the PTFE filter must not be damaged, drilled or removed.

The PTFE filter must never be touched with bare hands as this alters the properties of the filter.

It is recommended to mount the head with the filter directed to the floor; horizontal mount is permitted but it should be considered that in this orientation, in case of external use, the head is more subjected to be in contact with water and/or deposit of dust.

It is forbidden to mount the head with filter directed to the ceiling because with this orientation any dust or dirt can block the filter and then possibility to detect gas.

5.1 I/O Connections

CYBER 4-20mA products could be configured with possibility to manage different output connections based on the type of specific request of the customers. It is possible to select up to 4 different signals to be connected to the output connector, indeed VCC and GND wires are fixed. XIN and DIN versions, differently have a fixed wiring connection. Here is following a list of the standard signal managed with CYBER 4-20mA and XIN/DIN products:

CYBER 4-20mA Head	XIN Head	DIN Head
VCC (12/24V)	VCC (12/24V)	VCC (12/24V)
GND	GND	GND
RS485-A	RS485-A	RS485-A
RS485-B	RS485-B	RS485-B
4-20 mA output signal	4-20 mA output signal	
Fault		_

Connector type: AMPMODU II 280365-0 Mating connector: AMPMODU II 280384-1

Example of the possible wire assembly that could be available with CYBER 4-20mA head:



Wire colour	Meaning
Red	Vcc (12/24 Vdc)
Black	GND
Green	RS485—B
White	RS485—A
Blue	4-20 mA output signal
Brown	Fault



Example of the possible wire assembly that could be available with XIN head:



Meaning
Vcc (12/24 Vdc)
GND
RS485—A
RS485—B
4-20 mA output signal

Example of the possible wire assembly that could be available with DIN head:



5.2 Safety data

CYBER 4-20mA and XIN/DIN products have been designed to be used in applications requiring SIL Capability. Based on the different type of configuration chose, specific values of SIL Capability have been obtained. Please refer to the specific document to check each value or ask to technical support to receive the related information.

5.3 4-20 mA output connection

- > Use shielded cables in case it is needed to reduce EMC interference
- Wires' cross section depends on the distance between the control panel and the detector: for a distance up to m 100 we advise a 3-core wire with cross section area of 0.75 mm2; for a distance between m 100 and 200 we recommend a 3-core wire with cross section of 1.0 mm2; for a distance between m 200 and 300 we recommend a 3-core wire with cross section 1.5 mm2.
- Should any junctions be necessary on wires, please make sure there is no interruption on the shield (in case of cable version head).
- Please remember that the shield is to be grounded from the control panel side only. Also remember never to connect the shield to the detectors.



- Ensure the wire connections, either clutching or crimping type, are properly carried out with terminals that do not oxidise or loosen. We recommend having them soldered.
- The CYBER 4-20mA and XIN gas sensors can be connected to control panels available on the market having 4-20mA input signals.

5.4 RS485 digital connection

The connection of detector head to RS485 bus lines should be performed by using a 4-wire cable, 1 pair for the RS485 bus and 1 for the power supply.

It is also necessary that:

- Wiring between the detector and the control panel should be made by using connection cable EIA RS485: 2 core wires with section 0.22 / 0.35 mm2 and shield (twisted pair). Nominal capacity between the wires <50pF/m, nominal impedance 120 Ω. These features can be found in BELDEN cable 9842 or similar (data transmission cable in EIA RS485).
- Using this wiring, the total length of the line should not exceed 1000 m.
- Make sure that each multi-polar wire includes just one RS485.
- Make sure that a 120 Ω end line resistor is placed at the beginning and at the end (on the last sensor) of the bus line.
- For the power supply connection, we recommend using a 2-wire cable with suitable section according to the distance and number of detectors. Once the installation has been completed, verify that each detector reaches at least 12 Vdc.

When sensors are RS485 connected, the proportional 4-20mA output remains active (if present).

Please refer to the specific Modbus communication protocol for any additional information.

6.0 Testing and use 6.1 Power on

When the detector is powered on, output current is nearly 1.5 mA.

After nearly two minutes, the output current is 4.0mA.

Once the warm-up phase is over, the detector can work correctly, although the optimal performances will be achieved after one hour.

6.2 Testing

Detectors are factory calibrated for the specific gas required by the customers. Future adjustment of the pre-set calibration can be carried out through digital communication.

IMPORTANT!

Check the functionality at least one time per year, by testing detector response with gas application.

Testing / initial checking and calibration should be carried out by using a gas mixture in the appropriate range, along with our calibration kit.

To execute this operation, the user must use the proper test gas bottle and connect to this the valve with flowmeter. Connect a pipe with adequate diameter, which connects to the calibration adapter for the gas detector. The calibration of the detector is made by handheld



calibration keypad or the related calibration SW. Ask to N.E.T for more details about the accessories for calibration.

Please consult the specific instruction manuals (keypad) for further information on use. We recommend recalibrating hydrocarbon detector with Infrared technology in both zero and span condition, zero calibration should be made applying Nitrogen, in case zero calibration will be performed in ambient air then span calibration should be performed applying target gas using a nafion tube interposed between calibration gas cylinder and detector head.

6.3 Use

The detector works autonomously and automatically. Once adequately connected, no further operations are required.

CYBER 4-20mA detector is equipped with an overrange indication which is activated when the gas concentration exceeds 100% of the full scale or when the sensor signal is lower than the zero-calibration value.

7.0 Maintenance

It is recommended that maintenance activities will be performed by trained staff following EN 60079-17 criterion.

7.1 Preventive maintenance routines

The preventive maintenance routines can be carried out according to EN/IEC 60079-17 Standard. Moreover, all industrial gas detectors for flammable gases or for toxic gases must be verified with a test mixture every one or three months according to the installation and plant type and according to the work duty.

7.2 Corrective maintenance routines

If any anomalous conditions occur during test operations, please repeat the test phase. Should the detector not react to the gas it has been calibrated for, please send it back to your supplier, for him to return it to the manufacturer or to a N.E.T. authorized technical centre for the repair.

7.3 Note on IP grade

Please note that the IP rating indicated on the instrument label does not imply that the equipment will detect gas during and after exposure to those conditions of dust and water intrusion. If exposed to the condition's representative of the IP rating, the equipment should be checked and recalibrated with a higher frequency and in case of damage of the IP protection cap, it must be replaced. The PTFE filter of the IP protection cap should by no means be touched by bare hands as this may alter the protection and the response in gas.



7.4 Cleaning

The detectors must be kept clean of dust deposits. Cleaning must be performed with damp cloths or with cloths that do not accumulate electrostatic charges. It is strictly forbidden the dust cleaning using compressed air.

7.5 Disassembly instructions

Power the unit off, disconnect the wires on the terminals and dismount the housing from any blocking systems.

The opening of sensor head can be conducted in safe zone and without power source. After 10 minutes from power source interruption, the equipment can be opened. It is strictly recommended the use of personal protective equipment during operations inside the enclosure.

7.6 Trouble shooting guide

The following table lists all error messages, which can be encountered, with corrective actions to resolve them. When the detector is in error status the 4-20 mA output is 2mA.

CYBER 4-	CYBER 4-20mA Error Name	Error Description	Corrective action
20mA Error Code			
0x00	NO_ERRORS	No error present	None
0x01	HEATING	Warmup state condition	Wait 2 minutes
0x02	E2PROM_ERROR	Internal E2PROM error	Turn power off, then on again.
0x03	FLASH_ERROR	Internal FLASH error	If the previous action does not resolve the error, please contact
0x04	RAM_ERROR	Internal RAM error	N.E.T.
0x05	VCC_ERROR	Power voltage below 10V or above 30V	Adjust detector power (10-30 V interval)
0x08	VGND_ERROR	Internal voltage out of limits	 Turn power off, then on again. If the previous action does not
0x0A	E2PROM_CKSM_ERROR	E2PROM Checksum error	resolve the error, please contact N.E.T.
0x0B	CHANGE_SENSOR	Sensing element out of date	Sensing element life time is expired, please contact N.E.T
0x0C	ANALOG_OUT_ERROR_4_20ma	4-20 mA error. Open loop or fault on analog output	Restore 4-20 mA loop
0×0E	ADC_ERROR	ADC reading out of limits	 Turn power off, then on again. If the previous action does not resolve the error, please contact N F T

Table 3) Error messages with their corrective actions for CYBER 4-20mA

Table 4) Error messages with their corrective actions for XIN/DIN Head			
XIN/DIN Error Code	XIN/DIN Error Name	Error Description	Corrective action
0x00	NO_ERROR	None	None
0x02	E2PROM_CKSM_ERROR	Internal E2PROM error	
0x03	FLASH_CKSM_ERROR	Internal FLASH error	
0x04	RAM_ERROR	Internal RAM error	Turn power off, then on again.
0x05	VDD_ERROR	Internal Power supply fail	 If the previous action does not resolve the error, please contact
0x06	I2C_ERROR	Internal communication error	N.E.T.
0x08	SPI_ERROR	Internal communication error	
0x09	VREF_ERROR	Internal Vref error	



CYBER 4-20mA/XIN-DIN Plastic IP65 Head INSTRUCTION MANUAL

MT5059 Rev.2

0x0A	DAC_ERROR	Internal DAC error	
0x0C	ANALOGUE_4- 20MA_ERROR	Output voltage does not correct	
0×0E	ADC_ERROR	Internal ADC error	
0x0F	SW_ERROR	Internal calculation error	
0x10	VIN_ERROR	Power supply level not correct	Verify input power that meets Sensor's power supply range
0x11	FLASH_READ_ERROR		
0x12	FLASH_WRITE_ERROR	Internal FLASH error	 Turn power off, then on again. If the previous action does not
0x13	FLASH_ERASE_ERROR		resolve the error, please contact
0x14	E2PROM_WRITE_ERROR	Internal E2PROM error	
0x16	RFI_ERROR	Internal signals not stable	Verify if Electromagnetic disturbances are present in the working environment.
0x17	VBG_ERROR	Internal Band gap error	Turn power off, then on again.
0x18	LAMP_ERROR	IR LAMP not work	 If the previous action does not resolve the error, please contact
0x19	AMP_ERROR	OP AMP not work	N.E.T.

CYBER 4-20mA product also manages another type of information that is related to the status of the head. Inside the following table are indicated status of the detector and the related codes:

Table 5) Status indications for CYBER 4-20mA	
--	--

CYBER 4-20mA Status Code	CYBER 4-20mA Status condition	Error Description
0x00	NO_ALARM	None
0×01	FAULT	Head is in error condition, please refer to Table 3 to identify the specific error condition and the related action.
0x02	THRESHOLD 1	Gas concentration is above threshold 1 limit
0x04	THRESHOLD 2	Gas concentration is above threshold 2 limit
0x08	THRESHOLD 3	Gas concentration is above threshold 3 limit
0x10	OVERRANGE	Gas concentration is above 100%Full scale

XIN/DIN products, differently from CYBER 4-20mA indicate presence of warning condition but is not indicating any status of the head.

Inside the following table are indicated warning of the detector and the related codes:

Table 6) Warning messages with their descriptions for XIN/DIN Head			
XIN/DIN Warning Code	XIN/DIN Warning Name	Warning Description	
0x00	NO_WARNING	(no warning, functioning ok)	
0x01	WARMUP_WARNING	(warm-up)	
0x02	INVALID_ACTIVE_WARNING	active not included within the functional limits expected)	
0x04	INVALID_REFERENCE_WARNING	(REF not included within the functional limits expected)	
0x08	INVALID_TEMPERATURE_WARNING	(TEMP not included within the functional limits expected)	
0x10	INVALID_READINGS_WARNING	active and reference signals changed too fast. This condition can happen in case of fast gas flow rate transient, fast temperature changes and presence of radio frequency, interferences. In case this flag is active then gas concentration is freezed)	
0x20	INVALID_ACTIVERMS_WARNING	(WRONG VALUES on the active channel. Active signal is too low)	
0x40	INVALID_REFERENCERMS_WARNING	(WRONG VALUES on the reference channel;. Reference signal is too low)	



0×80	HW_TEST_WARNING	(HW test in progress. It is performed once per day)

8.0 **Restorations**

Restorations are not allowed; the user must give the entire equipment to the manufacturer with the RMA number required in advance to return the goods.

9.0 Packing instructions

To grant a stout protection against impacts we recommend using the original package or protect the device with bubble wrap sheets.

10.0 Warranty for repairing

Warranty on N.E.T products is valid one year from the delivery date placed on transportation documents. Defective products can be returned to N.E.T. Srl only after a previous agreement and with a description of the fault. N.E.T. Srl has the right to replace or repair all the products that, according to his unquestionable judgement, are found to be defective, without being held responsible for any possible direct or indirect damages suffered by the Customer. According to the above-mentioned warranty, shipping and packaging charges and any other incidental expenses for the products returned to N.E.T. Srl will be at the Customer's own risk and charged to him. This warranty however is not valid for articles that have been broken, repaired by a third person or not used according to the instructions contained in this document or supplied with the products, related to the storage, installation, operation, maintenance, or servicing of the products.

IMPORTANT!

Please be aware that all perishables installed in our products (sensors) benefit only of the warranty conditions stated by the original manufacturer.

11.0 Instructions for disposal

When the device reaches the end of its life, it should be disposed of in accordance with local waste management requirements and environmental legislation. Employed materials are subdivided into the following categories:

- Sensor head enclosure: plastic
- > Electronic boards: Waste Electrical & Electronic Equipment (WEEE)
- Sensing element: Waste Electrical & Electronic Equipment (WEEE)

N.E.T has a policy of continuous development and improvement of its products. As such the specification for the device outlined in this document may be changed without notice. In case of modification of the product, N.E.T disclaims all liability. Data may change, as well as legislation and you are strongly advised to obtain copies of the most recently issued regulations, standards, and guidelines. This publication is not intended to form the basis of a contract. No part of this publication may be reproduced, distributed, or transmitted in any form or by any means, including photocopying, recording, or other electronic or mechanical methods, without the prior written permission of N.E.T.

Contact details: N.E.T s.r.l. Via Campania, 5 - 20006 – Pregnana Milanese (MI) Italy TEL. +39 0293544190 - www.nenvitech.com - E-mail: info@nenvitech.com

